

4G GPS **SOS WRISTBAND**



MODEL# SOS100


USER GUIDE

Visit: www.SecuLife.us





	CHAPTER 1	3
	QUICK SETUP GUIDE	4
READ ME	GETTING STARTED	5
	CHAPTER 2	
READ ME		
_	CHARGING	
	SOS BUTTON	13
	ANSWER A CALL BUTTON	14
	SPEED DIAL BUTTONS	15
	CHAPTER 3:	10
	MAP PAGE	17
	NOTIFICATIONS	18
	MY DEVICES	19
	DEVICE DETAILS	2
	CREATE A GEO FENCE	2
	CREATE A WIFI FENCE	
	LOCATION HISTORY	2
READ ME	SET CONTACT INFO	2
	SMS ALERT SWITCH	2
	SET SOS NUMBER	2
	REMOTE CALL/ EAVES DROP	2
	ANSWER MODE	2
	PHONEBOOK	2
	QUESTIONS	31
	SAFETY INFORMATION/WARNING/CAUTION	3



AN OVERVIEW ON THE QUICK INITIAL SETUP GUIDE

KEEP YOUR LOVED ONES SECURE AND INDEPENDENT BOTH AT HOME AND ON THE GO.

QUICK SETUP GUIDE

ACTIVATE YOUR SERVICE PLAN ONLINE
RECEIVE A NEW PHONE NUMBER FOR
YOUR SOS WRISTBAND

SWITCHING DEVICE ON AND OFF
WITH A SIMPLE PRESS OF A BUTTON

TO REMOTELY MONITOR YOUR LOVED

USE THE USERNAME AND PASSWORD YOU ENTERED DURING ACTIVATION, THEN

5 SET THE CORRECT INFO OF THE DEVICE WEARER AND THE APP USER



ACTIVATE YOUR SERVICE PLAN ONLINE

YOUR SECULIFE® SOS
WRISTBAND COMES WITH A
PREINSTALLED SIM CARD;
THE SIM CARD NUMBER IS
LOCATED ON THE BOX.
ACTIVATE THE SERVICE
PLAN ON YOUR SIM ONLINE
AND RECEIVE A NEW PHONE
NUMBER ASSOCIATED WITH
THE SOS WRISTBAND.



VISIT: WWW.ACTIVATE.SECULIFE.US

WE WILL REGISTER YOUR EMAIL ADDRESS AND LINK THE DEVICE TO OUR SECULIFE® MOBILE APP WHEN ACTIVATING YOUR DEVICE SIM CARD, SO YOU DON'T HAVE TO MANUALLY REGISTER TO THE APP. YOU'LL RECEIVE AN EMAIL CONFIRMATION WITH THE NEW NUMBER FOR YOUR RECORDS AND TO BE USED TO UPDATE YOUR MOBILE APP DEVICE INFO ON THE FOLLOWING STEPS.

2

TURN ON THE SOS WRISTBAND

PRESS AND HOLD THE SOS BUTTON ON THE WRISTBAND FOR 10 SECONDS



IF THE SOS WRISTBAND DOESN'T TURN ON, IT LIKELY NEEDS TO BE CHARGED. CHARGE THE SOS WRISTBAND FOR SEVERAL HOURS AND THEN TRY AGAIN.



3

DOWNLOAD THE MOBILE APP

TO DOWNLOAD, SCAN THE QR CODE BELOW FROM YOUR CELLPHONE:



SECULIFE



Scan QR Code



Scan QR Code or Android Device



www.Seculife.us/ios



www.Seculife.us/android

OUR MOBILE APP IS ALSO AVAILABLE ON APPLE APP STORE OR GOOGLE PLAY STORE. SEARCH "SECULIFE" TO FIND THE APP.



Л

LOGIN TO THE MOBILE APP

A FAMILY MEMBER OR THE CAREGIVER CAN OPEN THE MOBILE APP AND LOGIN TO THEIR ACCOUNT WITH A USERNAME AND PASSWORD THAT WAS CREATED DURING THE SIM CARD ACTIVATION PROCESS ONLINE.

- ENTER YOUR EMAIL ADDRESS AS USERNAME.
- · ENTER YOUR PASSWORD.





UPDATE

UPDATE THE DEVICE INFO ON YOUR MOBILE APP

WHEN YOU FIRST ACTIVATE YOUR SOS WRISTBAND'S SIM CARD ONLINE, THE DEVICE WILL BE ADDED INTO YOUR MOBILE APP ACCOUNT AUTOMATICALLY, YOU CAN ACTIVATE MULTIPLE DEVICES ONLINE, MAKE SURE YOU USE THE SAME EMAIL ADDRESS OF YOUR MOBILE APP IN ORDER ADD THE DEVICE UNDER YOUR MOBILE APP LOGIN ACCOUNT.

- 1. TAP ON YOUR DEVICE TO GO TO THE DEVICE DETAILS TO SET/UPDATE ITS SETTINGS.
 2 SET MAIN CONTACT NUMBER.
- THE PERSON'S (ADMIN'S) PHONE
 NUMBER, CARING FOR THE
 SENIOR, TO RECEIVE APP
 ALERTS.
- 3. SET SOS NUMBER: LIST OF PHONE NUMBERS TO RECEIVE NOTIFICATION ALERTS WHEN THE SOS BUTTON IS TRIGGERED.



You will see the device (s) you added here, click to set and update the information.



DETAILED INFO OF THESE STEPS CAN BE FOUND IN CHAPTER 3 OF THIS MANUAL.



MEET YOUR SECULIFE® SOS SMART WRISTBAND

A GAME-CHANGING, PERSONAL SECURITY MONITORING SYSTEM FOR THOSE WHO MATTER MOST IN YOUR LIFE!

MEET YOUR SOS SMART WRISTBAND



BACK



Use Device IMEI to Add A New Device Manually

THE FOLLOWING TABLES DESCRIBE THE LED LIGHTS



WHEN POWERED ON

Network Indicatore

Slow Blinking | Signal Searching Fast Blinking Signal Received

WHILE CHARGING

Slow Blinking Device is Charging

Fully Charged



WHEN POWERED ON

GPS Indicator

Slow Blinking GPS Positioning Fast Blinking Position Uploaded

WHILE CHARGING

Slow Blinking Device is Charging Solid Red Fully Charged

Solid Red



CHARGING

USE ONLY THE SECULIFE® AUTHORIZED MAGNETIC CHARGING

FIRST TIME CHARGE

WE RECOMMEND FULLY CHARGING THE SOS WRISTBAND FOR 8-HOURS BEFORE USING IT FOR THE FIRST TIME. IN THE MEANTIME, YOU CAN ACTIVATE THE SIM CARD THAT COMES WITH THE SOS WRISTBAND IF YOU HAVEN'T DONE IT YET.

CHARGE YOUR DEVICE

CONNECT THE MAGNETIC CHARGING CABLE TO THE CHARGING PORT LOCATED ON THE BACK OF THE WRISTBAND AND LET IT CHARGE FOR AT LEAST 4-5 HOURS.



AVOID LEAVING THE MAGNETIC CABLE PORT ON METAL SURFACES TO AVOID A SHORT CIRCUIT THAT MIGHT CAUSE DAMAGE OR FIRE.

SOS BUTTON

SOS WILL IMMEDIATELY CONTACT THE EMERGENCY CONTACT LIST AND SEND AN SMS ALERT AND IN-APP ALERT.

TO ACTIVATE THE SOS ON THE DEVICE, HIT THE SOS BUTTON FOR 5 SECONDS.

UPON TRIGGERING THE SOS BUTTON BY THE DEVICE WEARER, THE MOBILE APP WILL RECEIVE AN IMMEDIATE NOTIFICATION OF THE WEARER'S LOCATION AND ITS SOS STATUS. UPON RECEIVING AN SOS ALERT, YOU CAN IMMEDIATELY SEE HIS/HER LOCATION ON THE MAP, CALL YOUR LOVED ONE TO ENSURE SAFETY. DURING EMERGENCY, WHNE SOS FUNCTION IS ACTIVATED, THEEE DEVICE WILL ALSO CALL THE PRESET SOS NUMBERE LIST.

SOS BUTTON HAS OTHER FUNCTIONS BESIDES SENDING THE SOS ALERTS. FOR EXAMPLE, DURING A PHONE CALL, PRESS ON SOS BUTTON ONCE TO HANG UP THE CALL. SEE BELOW FUNCTIONS

SOS BUTTON FUNCTIONS

Tap Once

- Announces the time
 Hangup ongoing call
- Press and Hold for 5 seconds
- Sends in-App SOS AlertCalls the SOS contacts
- Press and Hold for 10 seconds
- Turn On / Off the device

SOS BUTTON





ANSWER A CALL BUTTON

WHEN RECEIVING A PHONE CALL, PRESS ON THE VOICE MESSAGE BUTTON TO ANSWER THE INCOMING CALL; IF THE DEVICE "ANSWER MODE" IS SET TO "PRESS TO ANSWER."





SPEED DIAL BUTTONS

THERE ARE TWO EASY-TO-USE SPEED DIAL BUTTONS TO QUICKLY CALL THE PERSONS ON YOUR PHONE BOOK DURING AN EMERGENCY OR WHEN YOU NEED TO CALL AND STAY IN TOUCH.

- SPEED DIAL 1: PRESS TO CALL THE FIRST CONTACT SAVED ON MOBILE APP'S PHONE BOOK
- SPEED DIAL 2: PRESS TO CALL THE SECOND CONTACT SAVED ON THE MOBILE APP'S PHONE BOOK





A NEW, NEXT-LEVEL, AND EASY WAY TO PROTECT AND CONNECT WITH YOUR LOVED ONE. ANYTIME, ANYWHERE!



THE DEVICE(S) LAST SEEN LOCATION ON THE MAP. MOBILE APP ALSO HAVE OTHER FUNCTIONS AVAILABLE (ADD FENCES, NOTIFICATIONS, MY DEVICES) ON THE FUNCTION BAR TO TRACK, LOCATE AND SETUP THE SOS



MY DEVICES PAGE.

MOBILE APP.



NOTIFICATIONS

SEE ALL THE NOTIFICATION RECEIVED FROM YOUR DEVICE

SEE THE ALERT TYPE AND THE DEVICE NAME WITH THE DATE & TIME OF THE ALERT.

IF YOU HAVE MULTIPLE DEVICES ADDED TO YOUR MOBILE APP, YOU WILL SEE ALL THE NOTIFICATIONS FOR ALL OF YOUR DEVICES FROM THIS NOTIFICATION PAGE. TO SEE THE NOTIFICATIONS OF A SPECIFIC DEVICE ONLY, YOU CAN GO TO:

NY DEVICES >> SELECT A DEVICE >> NOTIFICATIONS BUTTON ON THAT PAGE.



Settings

MY DEVICES

FROM YOUR MOBILE APP HOME SCREEN, TAP ON
"MY DEVICES" TO SEE LIST OF DEVICES, IF YOU HAVE
MULTIPLE DEVICES. CLICK ON THE DEVICE TO GO TO THE
"DEVICE DETAILS".

Click on + to Add a new Device

From My Devices page you will see

- Device Name (The name can be changed from Device Details)
- Battery level
- Device SIM card and IMEI #
- Last seen date/time.

Click on a device to go to "Device Details" to setup and update the device information at anytime.

*Device status Types

- Online: This is when Device status indicates its online and connected to the App.
- Offline: This is when the device is switched off or no network signal is detected.



Click "My Devices" to see your device list

Settings

DEVICE DETAILS

FROM YOUR MOBILE APP HOME SCREEN, TAP ON
"MY DEVICES" THEN CLICK ON THE DESIRED DEVICE TO
ACCESS AND TO GO TO ITS "DEVICE DETAILS".
NOTIFICATIONS | HISTORY | SETTINGS WILL BE EXPLAINED
ON THE FOLLOWING PAGES ON THIS CHAPTER

GEO FENCES:

SELECT THE DESIRED GEO-FENCE (SUCH AS HOME, DOCTOR'S OFFICE, PARK_ETC.), THAT YOU PREVIOUSLY CREATED, TO RECEIVE ALERTS WHEN THE DEVICE ENTERS OR LEAVES THESE AREAS.

WIFI FENCE:

RECEIVE ALERTS WHEN THE DEVICE ENTERS OR LEAVES A WIFI RANGE OF A SELECTED WIFI NETWORK.

TRACKING INTERVAL.

SET UP LOCATION UPLOAD INTERVALS. THIS IS HOW OFTEN DO YOU WISH THE DEVICE TO REPORT THE LOCATION. WE SUGGEST TO SETUP TO 12 HOURS TO ENHANCE BATTERY-SAVING MODE: THIS WILL ENSURE THE DEVICE HAS SUFFICIENT BATTERY POWER FOR ANY POTENTIAL SOS ALERTS.





GEO-FENCE

GEO FENCING, ALSO KNOWN AS "SAFE ZONES," CAN BE SET UP FROM THE MOBILE APP; YOU CAN ADD, EDIT OR REMOVE A GEO-FENCE AREA. ONCE A GEO FENCE IS CREATED YOU CAN SELECT THE FENCE(S), FROM DEVICE DETAILS PAGE, TO RECEIVE ALERTS WHEN ENTERING OR EXITING A GEO-FENCE AREA.

ADD GEO FENCE:

- CLICK ON NEW FENCE BUTTON FIRST THEN SET A PERIMETER ON THE MAP
- CLICK ON SAVE BUTTON AND ENTER THE FENCE NAME (SUCH AS HOME, DOCTOR'S OFFICE, PARK... ETC.).
 RECOMMENDED GPS RADIUS OF 1000

FEET OR HIGHER TO REDUCE FALSE ALERTS.

YOU CAN SETUP MULTIPLE GEO FENCE LOCATIONS AS NEEDED.

DELETE GEO FENCE:

 TO DELETE A GEO FENCE, CLICK ON THE DESIRED FENCE FIRST, THEN CLICK ON DELETE BUTTON

CLICK TO ADD OR DELETE FENCES.





WIFI FENCE

THIS FEATURE IS AVAILABLE ON OUR SOS WRISTBAND DEVICE. SELECT A WIFI FENCE ON YOUR DEVICE DETAILS AND RECEIVE ALERTS WHEN THE DEVICE LEAVES THE WIFI RAGE.

SELECT THE WIFI FROM THE DROP-DOWN LIST.

PLEASE NOTE: THE WIFI IN THE SOS WRISTBAND DOESN'T SUPPORT A 5G-WIFI CONNECTION

- ANDROID PHONES SHALL CHOOSE 2.4G WIFI AS THE HOTSPOT OF THE WIFI FENCE.
- IF YOU ARE USING THE MOBILE APP ON YOUR IPHONE, YOUR PHONE WILL CONNECT TO THE WIFI AND WILL SET IT AS THE WIFI FENCE HOTSPOT AUTOMATICALLY.

IF YOUR IPHONE IS CONNECTED TO A 5G-WIFI, PLEASE SWITCH YOUR WIFI CONNECTION ON YOUR IPHONE TO 2.4G FIRST; OTHERWISE, DON'T SET A WIFI FENCE TO AVOID SETTING A NON-FUNCTIONING WIFI FENCE; THIS WILL PREVENT FALSE ALARMS.





LOCATION HISTORY

THE HISTORICAL ROUTE, ALSO KNOWN AS LOCATION HISTORY, WILL DISPLAY THE HISTORICAL ROUTE OF ANY DAY WITHIN THE PAST 365 DAYS. TO HELP YOU SEE THE PRESENT AND PAST PLACES VISITED.

SELECT A DATE TO SEE THE TRACKING HISTORY.

CLICK ON ANY OF THE PINPOINTS TO VIEW THE TIMESTAMP OF THE TRACKED EVENT.



SET CONTACT INFO



FROM YOUR MOBILE APP HOME SCREEN, TAP ON DEVICES SELECT YOUR DEVICE, CLICK ON "SETTINGS" THEN "SMS

ALERTS PHONE#" & "ALERTS E-MAIL"

ADMIN

SMS ALERTS PHONE:

THE PERSON'S PHONE NUMBER WHO WILL BE RECEIVING ALERTS FORM THE DEVICE.

ALERTS E-MAIL:

THE PERSON'S EMAIL ADDRESS WHO WILL BE RECEIVING ALERTS FORM THE DEVICE.



UPDATE

MAKE SURE TO SCROLL DOWN AND SAVE THE CHANGES BY CLICKING ON THE "UPDATE" BUTTON



FROM YOUR MOBILE APP HOME SCREEN, TAP ON DEVICES SELECT YOUR DEVICE, CLICK ON "SETTINGS". YOU WILL SEE THE OPTIONS TO CHOOSE YOUR ALERTS OPTIONS.

ENABLE THE THESE ALERTS TO SET THE DEVICE TO SEND Settings SMS/EMAIL/IN-APP NOTIFICATION Shelley sos wristband ALERTS TO THE PHONE# & FMAIL Time Zone YOU'VE SET (MONITORING) Eastern PERSONNEL AND RECEIVE IN-APP SOS Alerte NOTIFICATIONS **BATTERY ALERTS:** Battery Alerts: CHOOSE HOW YOU WISH TO RECEIVE YOUR ALERTS (EMAIL, SMS Removal Alerts: OR IN-APP NOTIFICATION) Gen-Fence Alerts Fall Down Alerts: SOS Phone#: 2139251121 GEO-FENCE ALERTS: CHOOSE HOW YOU WISH TO RECEIVE YOUR ALERTS (EMAIL, SMS SMS Alerts Phone

RECEIVE YOUR ALERTS (EMAIL, SMS OR IN-APP NOTIFICATION) EVERYTIME THE DEVICE ENTERS OR LEAVES THE GEO FENCE AREA

EAVES THE GEO FENCE AREA

UPDATE

ON THE "UPDATE" BUTTON



SET SOS NUMBER

FROM YOUR MOBILE APP HOME SCREEN, TAP ON DEVICES SELECT YOUR DEVICE, CLICK ON "SETTINGS" THEN "SOS PHONE #"

SET SOS PHONE NUMBER:

LIST OF THE PHONE NUMBER(S) TO RECEIVE NOTIFICATION SMS AND CALLS WHEN THE SOS BUTTON IS TRIGGERED.

YOU CAN SET UP-TO 3 PHONE NUMBERS.

SOS E-MAIL:


SET THE EMAIL TO RECEIVE THE SOS ALERTS WHEN TRIGGERED.



UPDATE

MAKE SURE TO SCROLL DOWN AND SAVE THE CHANGES BY CLICKING ON THE "UPDATE" BUTTON





SIMPLY CLICK ON CALL BUTTON FROM THE DEVICE SETTING PAGE THIS FEATURE WILL ALLOW YOU TO EAVESDROP ON YOUR LOVED ONE TO CHECK IF THEY ARE SAFE.

THE NUMBER YOU ENTER WILL RECEIVE A CALL FROM THE DEVICE TO ALLOW YOU TO LISTEN-IN ONLY. THE END USER WILL NOT BE ABLE TO HEAR YOU.





ANSWER MODE

FROM YOUR MOBILE APP HOME SCREEN, TAP ON DEVICES SELECT YOUR DEVICE, CLICK ON "SETTINGS". TO CHOOSE HOW YOU WISH THE DEVICE TO ANSWER AN INCOMING PHONE CALL.

- PRESS TO ANSWER: ALLOW YOUR LOVED ONE TO ANSWER A CALL AT THE COMFORT OF THEIR WRISTBAND WITH ONE TOUCH OF THE ANSWER CALL BUTTON FROM THEIR SOS WRISTBAND.
- HANDS-FREE AUTO-ANSWER: AUTO PICK-UP SPEAKERPHONE TO SPEAK TO YOUR LOVED ONE ANYTIME AND INSTANTLY KNOW WHEN YOUR LOVED ONE NEEDS YOU.

← Set	tings		
Main Contact	Susan's SOS	Writsband	
2	Number:		
SOS SMS Aler SOS Phone		ery SMS Ale	п 🥌
600000000			
2			
SOS E-Mail:			
-			
Remote Call /	Eaves Drop: 🔞)	
	CA	iLL	
Answering Mo	ide: 🕖		
_	ton to Answer	Hands Fre Answer	e Auto
Phone Book:	•		
61111111111			
n	æ		My Devices



MAKE SURE TO SCROLL DOWN AND SAVE THE CHANGES BY CLICKING ON THE "UPDATE" BUTTON



FROM YOUR MOBILE APP HOME SCREEN, TAP ON DEVICES SELECT YOUR DEVICE, CLICK ON "SETTINGS" THEN "PHONE BOOK"

LIMIT YOUR LOVED ONE'S CONTACTS TO ONLY KNOWN
FAMILY OR FRIENDS, AND THE MAIN PERSON CARING FOR
THE SENIOR MUST BE SET AS THE PRIMARY CONTACT
PHONE NUMBER

SAVE THE PHONE NUMBERS OF THE FAMILY/FRIENDS.

THE FIRST TWO NUMBERS ARE STORED IN THE SOS WRISTBAND SPEED DIAL KEY 1 & 2.

WHITELIST: ONLY NUMBERS IN THE PHONE BOOK CAN GET THROUGH THE CALLS TO SOS WRISTBAND, NUMBERS NOT LISTED HERE WILL NOT BE ABLE TO CALL THE NUMBER ASSIGNED TO THE DEVICE

Susan's SOS Witsband

Main Croset Number:

SOS SMA Alert
CALL

Accepted SMA Alert
Accepted SM

UPDATE

MAKE SURE TO SCROLL DOWN AND SAVE THE CHANGES BY CLICKING ON THE "UPDATE" BUTTON

.





CONTACT US
WWW.SUPPORT.SECULIFE.US



WATCH VIDEOS WWW.SECULIFE.US

SAFFTY INFORMATION

TO PREVENT INJURY TO YOURSELF AND OTHERS, OR TO AVOID DAMAGE TO THE DEVICE. FIRST READ ALL SAFETY INFORMATION BEFORE USE.

WARNING

- · USE MANUFACTURER-APPROVED ACCESSORIES AND SUPPLIES.
- · CAUTION ELECTRICAL OPERATED PRODUCT
- THIS PRODUCT IS NOT A TOY. KEEP OUT OF REACH OF CHILDREN AND PETS UNLESS PROPERLY SUPERVISED. THE PRODUCT CONTAINS SMALL PARTS THAT CAN BE A CHOKING HAZADD
- DO NOT DROP OR CAUSE AN IMPACT TO THE DEVICE.
- PREVENT THE CHARGING JACK AND CORD FROM COMING INTO CONTACT WITH CONDUCTIVE MATERIALS SUCH AS LIQUIDS, DUST, METALS, PENCIL LEAD. OR AEROSOLS.
- DO NOT STORE YOUR DEVICE IN
 EXTREMELY HOT OR IN EXTREMELY
 COLD AREA. RECOMMENDED TO USE
 YOUR DEVICE FROM 41F TO 95F
- DO NOT STORE YOUR DEVICE NEAR OR ON TOP OF HEATERS, MICROWAVES. HOT COOKING
- MICROWAVES, HOT COOKING EQUIPMENT, OR HIGH-PRESSURE CONTAINERS.
- DO NOT USE YOUR DEVICE WHILE CHARGING OR TOUCH WITH WET HANDS.
- THE DEVICE AND USB CABLE SHOULD BE PERIODICALLY EXAMINED FOR BREAKS, CRACKS, OR FRAYING, WHICH COULD RISK FIRE, ELECTRICAL SHOCK, OR PERSONAL INJURY. IF

DAMAGED, THE USB CABLE SHOULD BE REPLACED OR REPAIRED BEFORE

 KEEP OUT OF REACH OF CHILDREN AND PETS; SMALL PARTS ARE A CHOKING HAZARD.

CAUTION

- · DO NOT DISASSEMBLE, MODIFY, OR REPAIR THE UNIT.
- ANY CHANGES OR MODIFICATIONS
 TO YOUR DEVICE CAN VOID YOUR
 MANUFACTURER'S WARRANTY. IF
 YOUR DEVICE NEEDS SERVICING
- YOUR DEVICE NEEDS SERVICING, CONTACT CUSTOMER SUPPORT. • DO NOT DISASSEMBLE OR
- PUNCTURE THE BATTERY, AS THIS
 CAN CAUSE EXPLOSION OR FIRE
- DO NOT PAINT OR PUT STICKERS ON YOUR DEVICE. PAINT AND STICKERS

 CAN CLOG MOVING PAPTS AND
- PREVENT PROPER OPERATION.

 -IF YOU ARE ALLERGIC TO PARTS OF
 THE DEVICE, YOU MAY EXPERIENCE
 ITCHING, ECZEMA, OR SWELLING OF
 THE SKIN. WHEN THIS HAPPENS,
 STOP LUSING THE DEVICE AND
- CONSULT YOUR PHYSICIAN.

 · ALLOWING UNQUALIFIED
 PERSONNEL TO SERVICE YOUR
- DEVICE MAY RESULT IN DAMAGE AND WILL VOID YOUR MANUFACTURER'S WARRANTY.

